



computer two

computer two, Regulador de reactiva de 2 passos, IP 00

Code: R13820. DESCATALOGADO

- > Programa: 1.1
- > Relé d'alarma: No
- > Rang mesura (V): 400
- > Alimentació Vca: 230 Vca (FN)
- > N° Passos: 2
- > Corrent d'entrada: . . ./250 mA
- > Unitat maniobra: Contactor

Especificacions

AC power supply	
Installation category	CAT III
Consumption	3 VA
Frequency	50-60 Hz
Nominal voltage	230 V ~ ±15%
Mechanical characteristics	
Size (mm) width x height x depth	90 x 90 x 5 (mm)
Environmental characteristics	
Relative humidity (without condensation)	95%
Operating temperature	-10 ... +50 °C
Standards	
Certifications	UL
Electrical safety, Maximum height (m)	2000
Standards	IEC 61326-1 , IEC 61010-1 , UL 508
Current measurement circuit	
Nominal current (In)	0,25 A ~
Allowable overload	1,2 In
Permanent overload	1,2 In
Connection	Entre V2 i N
Voltage measurement circuit	
Nominal voltage	400 V ~ ±15%
Electrical safety	
Insulation	Protecció contra descàrregues elèctriques per doble aïllament classe II (CEI 61010)
Digital relay outputs	
Electrical life	10x10 ⁴ maniobras



computer two

Code: R13820.

Mechanical life

5x10⁶ maniobres

computer two
Relé de reactiva de 2 passos, IP 00

CODI	TIPUS	Unitat maniobra	Nº Passos	Corrent d'entrada
R13820.	computer two	Contactora	2	.../250 mA
R13821.	computer two	Contactora	2	.../250 mA
R13822.	computer two	Contactora	2	.../250 mA
R13823.	computer two	Contactora	2	.../250 mA

Requires the use of MC transformers (not included). See section M - Measuring current transformers and shunts