



computer two

computer two, Regulador de reactiva de 2 passos, IP 00

Code: R13823. DESCATALOGADO

- > Programa: 1,2,5
- > Relé d'alarma: No
- > Rang mesura (V): 400
- > Alimentació Vca: 230 Vca (FN)
- > N° Passos: 2
- > : .../250 mA
- > Unitat maniobra: Contactor

Especificacions

AC power supply

Installation category	CAT III
Consumption	3 VA
Frequency	50-60 Hz
Nominal voltage	230 V ~ ±15%

Mechanical characteristics

Size (mm) width x height x depth	90 x 90 x 5 (mm)
Weight (kg)	0,18

Environmental characteristics

Relative humidity (without condensation)	95%
Operating temperature	-10 ... +50 °C

Standards

Certifications	UL
Electrical safety, Maximum height (m)	2000
Standards	IEC 61326-1 , IEC 61010-1 , UL 508

Current measurement circuit

Nominal current (In)	0,25 A ~
Allowable overload	1,2 In
Permanent overload	1,2 In
Connection	Entre V2 i N

Voltage measurement circuit

Nominal voltage	400 V ~ ±15%
-----------------	--------------

Electrical safety

Insulation	Protecció contra descàrregues elèctriques per doble aïllament classe II (CEI 61010)
------------	---

Digital relay outputs

Electrical life	
-----------------	--



computer two

Code: R13823.

	10x10 ⁴ maniobras
Mechanical life	5x10 ⁶ maniobres

computer two
Relé de reactiva de 2 passos, IP 00

CODI	TIPUS	Unitat maniobra	Nº Passos	Corrent d'entrada
R13820.	computer two	Contactora	2	.../250 mA
R13821.	computer two	Contactora	2	.../250 mA
R13822.	computer two	Contactora	2	.../250 mA
R13823.	computer two	Contactora	2	.../250 mA

Requires the use of MC transformers (not included). See section M - Measuring current transformers and shunts