



CMC 7.5 B

CMC 7.5 B, Contactor

Code: R281A5.

- > Freqüència (Hz): 50 / 60
- > kvar (220-240V): 5
- > kvar (400-440-480 V): 7.5
- > kvar (500-550 V): 9
- > kvar (660- 690 V): 11
- > Tensió bobina (Vca): 230

Descripció

La sèrie **CMC-B** són contactors per connectar un o més condensadors. Amb un alt nombre d'operacions i una alta resistència elèctrica que els converteixen en uns contacters robustos i duradors.

Aplicació

Per a la connexió dun o diversos condensadors de potència.



CMC 7.5 B

Contactors per a condensadors de potència

Code: R281A5.

Especificacions

AC power supply

Frequency	50/60 Hz
Nominal voltage	220 ... 690 V

Electrical characteristics

Cadence of manoeuvre	240/h
Coil tension / tolerance	230 V / 0,85 ... 1,1 Un
Electrical lifetime	200000 cycles
Insulation voltage, circuit	690 ... 1000 V

Característiques elèctriques

Corrent operativa nominal	11 A (400 V)
---------------------------	--------------

Mechanical characteristics

Size (mm) width x height x depth	44.8 x 72.2 x 71 (mm)
Weight (kg)	0,28

Environmental characteristics

Protection class	IP 00
Relative humidity (without condensation)	5 ... 95 %
Operating temperature	-25 ... +55 °C

Standards

Certifications	VDE
Electrical safety, Maximum height (m)	2000
Standards	IEC 60947-4-1, VDE 0660

CMC B

Contactors CMC-B

CODI	TIPUS	Freqüència (Hz)	kvar (220-240V)	kvar (400-440-480 V)	kvar (500-550 V)	kvar (660-690 V)	kvar (660-690 V)
Maximum operating power (Kvar)							
R281A5.	CMC 7.5 B	50 / 60	5	7.5	9	11	
R281A6.	CMC 12 B	50 / 60	6.7	12.5	15		18
R281A4.	CMC 20 B	50 / 60	11	20	24	30	
R281A8.	CMC 32 B	50 / 60	14	25	30		35
R281A1.	CMC 40 B	50 / 60	20	30	35		40



CMC 7.5 B

Contactors per a condensadors de potència

Code: R281A5.

CODI	TIPUS	Freqüència (Hz)	kvar (220-240V)	kvar (400-440-480 V)	kvar (500-550 V)	kvar (660-690 V)	kvar (660-690 V)
R281A9.	CMC 75 B	50 / 60	29	50	60		70
R281A3.	CMC 85 B	50 / 60	32	60	70		80
R281AD.	CMC 150 B	50 / 60	45	80	100		115
R281AH.	CMC 150 D	50 / 60	45	80	100		115



CMC 7.5 B

Contactors per a condensadors de potència

Code: R281A5.

Dimensions

