



FB3-5-06

FB3-5-06, Filtre del tercer harmònic per a xarxa monofàsica (50 Hz)

Code: R78101. **DESCATALOGADO**

- > Sistema: Monofàsic
- > Freqüència (Hz): 50
- > Corrent màx. neutre: 6

Descripció

Els filtres FB3 són filtres de bloqueig del 3r harmònic, dissenyats per a la reducció del dit harmònic en instal·lacions amb càrregues monofàsiques distorsionants.

Aplicació

Per a càrregues monofàsiques com ara ordinadors personals, pantalles TFT, projectors, etc.



FB3-5-06

Filtre del tercer harmònic

Code: R78101.

Especificacions

AC power supply

Frequency	50 HZ (60 Hz bajo demanda)
Nominal voltage	220/240 Vca F-N

Mechanical characteristics

Size (mm) width x height x depth	204 x 310 x 233 (mm)
Weight (kg)	8

Environmental characteristics

Protection class	IP 23 (UNE-EN 60529)
Relative humidity (without condensation)	95%
Operating temperature	-10 ... +50 °C

Electrical characteristics

Maximum transient current	10 A (1 min seguit almenys de 5 min a nominal)
---------------------------	--

Current measurement circuit

Allowable overload	6 A (en el conjunt de tomes)
Permanent overload	6 A (in the set of sockets)

FB3
Filtre del tercer harmònic per a xarxa 50 Hz

CODI	TIPUS	Corrent màx. neutre
R78101.	FB3-5-06	6
Without box (IP 00)		
R78131.	FB3T-5-06-00	6
R78132.	FB3T-5-10-00	10
R78133.	FB3T-5-16-00	16
R78134.	FB3T-5-25-00	25
R78135.	FB3T-5-32-00	32
R78136.	FB3T-5-50-00	50
R78137.	FB3T-5-63-00	63
R78138.	FB3T-5-100-00	100
With box (IP 21)		
R78121.	FB3T-5-6-21	6
R78123.	FB3T-5-16-21	16
R78124.	FB3T-5-25-21	25



FB3-5-06

Filtre del tercer harmònic

Code: R78101.

CODI	TIPUS	Corrent màx. neutre
R78125.	FB3T-5-32-21	32
R78127.	FB3T-5-63-21	63
R78128.	FB3T-5-100-21	100