

FP GW LoRa-ETH

GW LoRa-ETH, GW-LoRa-Eth, Gateway LoRa-Ethernet,

Code: E83G020020200 **DESCATALOGADO**

Specifications

DC power supply

Installation category	CAT II 1500 V
Consumption	3.6 W
Nominal voltage	24 V ±10%

Environmental characteristics

Protection class	IP 00
Relative humidity (without condensation)	5 ... 95 %
Installation, location, position.	3000 m
Storage temperature	-25...+80 °C
Operating temperature	-25...+70 °C

Mechanical characteristics

Envelope	Self-extinguishing V0 plastic
Fastening	DIN rail
Weight (kg)	6,7

Current measurement circuit

Installation category	CAT II 1500 V
Impedance	0.5 mΩ
Minimum current measurement	0.1 A

Voltage measurement circuit

Installation category	CAT II 1500 V
Input impedance	2400 kΩ
Voltage measuring range	-25 ... -1500 Vdc
Maximum input voltage consumption	0,625 mA
Minimum measurement voltage (Vstart)	-25 V

Input

Accuracy	± 3°C
Range	-30 ... 100°C
Resolution	±0,1 mA
Type	Pt100/1000

Standards

Electrical safety, Maximum height (m)	3000
Electrical safety, Installation category	Protection against electric shock: Double class II insulation
Standards	EN 61000-6-2, EN 61000-6-4, EN 61010-1, EN 61010-2-30

Creation date: 04/11/2026 - CIRCUTOR, SAU reserves the right to make technical changes or modify the content/images of this document without prior notice, in order to improve its reliability, functionality, design or for other reasons.
It accepts no liability for any errors, inaccuracies or possible lack of information in this document.

FP GW LoRa-ETH

Code: E83G020020200

User interface

LED	4

Digital inputs

Input/output insulation	Optoisolated
Quantity	3
Type	Potential free contact
Maximum short-circuit current	3.2 mA
Maximum open circuit voltage	24 V

Kits GW-LoRa

LoRa Gateway

CODE	TYPE	Description
E83G020021100	FP KIT GW LoRa-ETH F868	Gateway LoRa-Ethernet communications kit 868 MHz, structure + base + anchors for mounting included
E83G020021200	FP KIT GW LoRa-ETH F915	Gateway LoRa-Ethernet communications kit 915 MHz, structure + base + anchors for mounting included
E83G020020100	GW LoRa-ETH-F868	GW-LoRa-Eth-F868, Gateway LoRa-Ethernet at 868 MHz
E83G020020200	FP GW LoRa-ETH	GW-LoRa-Eth, Gateway LoRa-Ethernet

The minimum configuration of the STM solution is made up of an STM-C module and an STM-S module

Creation date: 04/11/2026 - CIRCUTOR, SAU reserves the right to make technical changes or modify the content/images of this document without prior notice, in order to improve its reliability, functionality, design or for other reasons.
It accepts no liability for any errors, inaccuracies or possible lack of information in this document.