



2EC96 2x.../100V

2EC96 2x.../100V, Voltmeter

Code: M13831.

- > Scale: 90°
- > Accuracy: 1,5
- > Measurement Range (V): 2x.../100
- > Device: 2EC96
- > Modules: 96x96

Description

- Does not need an auxiliary power supply
- DIN box with dimensions 96 and 144 mm
- Class 1.5
- Double scale

Application

For the measurement and comparison of alternating currents from two generators or a generator in the network, when connected in parallel.



2EC96 2x.../100V

Voltmeter, marine applications equipment

Code: M13831.

Specifications

Mechanical characteristics

| | |
|----------------------------------|---------------------|
| Size (mm) width x height x depth | 96 x 96 x 49.2 (mm) |
| Fastening | Panel |
| Weight (kg) | 0,22 |

Environmental characteristics

| | |
|-----------------------|---|
| Protection class | Panel: IP 52 (Front), IP 00 (Terminals) |
| Storage temperature | -25 ... +40 °C |
| Operating temperature | +10 ... +30 °C |

Standards

| | |
|----------------|--|
| Certifications | CE |
| Standards | BS 89, UNE-EN 60051, IEC 144, DIN 43780, IEC 51, UNE 21318 |

Voltage measurement circuit

| | |
|---------------------------------------|---|
| Consumption | 1 ... 4 VA |
| Sampling frequency | 20 ... 100 Hz |
| Nominal voltage | 230 V ~ |
| Maximum permanent measurement voltage | 1,2 Vn permanent rated voltage / 2 Vn during 5s |

Electrical characteristics

| | |
|-----------------------------|---|
| Insulation voltage, circuit | 2kV a 50 Hz < 1min entre mecanismo y caja |
|-----------------------------|---|

Measurement accuracy

| | |
|----------|----------|
| Accuracy | 1,5 % FE |
|----------|----------|

2EC

Double voltmeters

| CODE | TYPE | Scale | Accuracy | Modules | Device |
|---------|-------------------|-------|----------|---------|--------|
| M13831. | 2EC96 2x.../100V | 90° | 1,5 | 96x96 | 2EC96 |
| M13832. | 2EC96 2x.../110V | 90° | 1,5 | 96x96 | 2EC96 |
| M13833. | 2EC96 2x220V | 90° | 1,5 | 96x96 | 2EC96 |
| M13834. | 2EC96 2x380V | 90° | 1,5 | 96x96 | 2EC96 |
| M13835. | 2EC96 2x440V | 90° | 1,5 | 96x96 | 2EC96 |
| M13841. | 2EC144 2x.../100V | 90° | 1,5 | 144x144 | 2EC144 |
| M13842. | 2EC144 2x.../110V | 90° | 1,5 | 144x144 | 2EC144 |
| M13843. | 2EC144 2x220V | 90° | 1,5 | 144x144 | 2EC144 |



2EC96 2x.../100V

Voltmeter, marine applications equipment

Code: M13831.

| CODE | TYPE | Scale | Accuracy | Modules | Device |
|---------|---------------|-------|----------|---------|--------|
| M13844. | 2EC144 2x380V | 90° | 1,5 | 144x144 | 2EC144 |
| M13845. | 2EC144 2x440V | 90° | 1,5 | 144x144 | 2EC144 |

Indicate the voltage transformer ratio



2EC96 2x.../100V

Voltmeter, marine applications equipment

Code: M13831.

Dimensions

