



## TC12 3200/5A

TC12 3200/5A, Current transformers narrow section

Code: M7038C. DESCATALOGADO

- > Flat strip(mm): 100 x 50
- > System: Single-phase
- > Class 0,5 Power (VA): 30
- > Class 1 Power (VA): 40
- > Class 3 Power (VA): 60
- > Measurement Range (A): 3200/5
- > Input current: 3200 A
- > Transformer type: Closed core

### Description

- Type: bar entrance
- Types: from 40 to 4000 A
- Internal diameter: from 20.3 to 63 mm, depending on the type
- Busbar dimensions: from 25 x 5 mm to 30 x 100 mm
- Individual certificate available on request
- DIN rail fixing accessory (Types **TC5** and **TC6**)
- Secondary coding types .../5 A (on demand .../1 A. **TC4** not available)

### Application

Converting a high nominal current to a lower current so that it can be measured by the unit. In installations where the electrical supply can be interrupted to install transformers.



## TC12 3200/5A

Current transformers narrow section

Code: M7038C.

### Specifications

#### Electrical characteristics

Safety factor (SF)	FS 5
Power	40 VA (Class 1)

#### Mechanical characteristics

Size (mm) width x height x depth	129 x 155 x 78 (mm)
Envelope	Plastic wrap V0 self-extinguishing, UL 94
Weight (kg)	1,119

#### Environmental characteristics

Thermal Class	Class B (+130 °C)
Protection class	IP 20
Relative humidity (without condensation)	15 ... 95 %

#### Specific technical characteristics of current sensors

Operating voltage	0,72 kV~ max.
-------------------	---------------

#### Current measurement circuit

Nominal frequency	50 / 60 Hz
Primary current measurement	3200 A
Dynamic current (Idyn)	2,5 Ith
Thermal short-circuit current (Ith)	60 In
Transformation ratio	... / 5 A

#### Standards

Standards	IEC 61869-1, IEC 61869-2, BS2627
-----------	----------------------------------

#### TC

Current transformers narrow section

CODE	TYPE	Measurement Range (A)	Flat strip(mm)	Class 0,5 Power (VA)	Class 1 Power (VA)	Class 3 Power (VA)
<b>TC4</b>						
M703D5.	TC4 50/5A	50/5	30 x 10  20 x 10  25 x 5	-	-	1
M703D6.	TC4 60/5A	60/5	30 x 10  20 x 10  25 x 5	-	-	1,25
M703D7.	TC4 75/5A	75/5	30 x 10  20 x 10  25 x 5	-	-	1,25
M703D8.	TC4 100/5A	100/5	30 x 10  20 x 10  25 x 5	-	2	3
M703D9.	TC4 125/5A	125/5	30 x 10  20 x 10  25 x 5	-	2,5	3,75



## TC12 3200/5A

Current transformers narrow section

Code: M7038C.

CODE	TYPE	Measurement Range (A)	Flat strip(mm)	Class 0,5 Power (VA)	Class 1 Power (VA)	Class 3 Power (VA)
M703DA.	TC4 150/5A	150/5	30 x 10  20 x 10  25 x 5	1,5	2,5	4
M703DB.	TC4 200/5A	200/5	30 x 10  20 x 10  25 x 5	2,5	5	6
<b>TC5</b>						
M70311.	TC5 40/5A	40/5	20 x 10  25 x 5  15 x 5	-	-	1,5
M70312.	TC5 50/5A	50/5	20 x 10  25 x 5  15 x 5	-	-	2,5
M70313.	TC5 60/5A	60/5	20 x 10  25 x 5  15 x 5	-	1,25	3,5
M70314.	TC5 75/5A	75/5	20 x 10  25 x 5  15 x 5	-	2	3,5
M70315.	TC5 100/5A	100/5	20 x 10  25 x 5  15 x 5	1,5	2,5	3,75
M70316.	TC5 125/5A	125/5	20 x 10  25 x 5  15 x 5	1,75	3,5	5
M70317.	TC5 150/5A	150/5	20 x 10  25 x 5  15 x 5	2,5	3,5	5
M70318.	TC5 200/5A	200/5	20 x 10  25 x 5  15 x 5	3,75	5	5
M70319.	TC5 250/5A	250/5	20 x 10  25 x 5  15 x 5	5	7,5	7,5
<b>TC5.2</b>						
M70321.	TC5.2 100/5A	100/5	20 x 12  25 x 10  30 x 10	-	1	1,5
M70322.	TC5.2 125/5A	125/5	20 x 12  25 x 10  30 x 10	-	1,5	2
M70323.	TC5.2 150/5A	150/5	20 x 12  25 x 10  30 x 10	1	2	2,5
M70324.	TC5.2 200/5A	200/5	20 x 12  25 x 10  30 x 10	2,5	3	3,5
M70325.	TC5.2 250/5A	250/5	20 x 12  25 x 10  30 x 10	3,5	3,75	5
M70326.	TC5.2 300/5A	300/5	20 x 12  25 x 10  30 x 10	3,5	3,75	5
M70327.	TC5.2 400/5A	400/5	20 x 12  25 x 10  30 x 10	3,5	5	7,5
M70328.	TC5.2 500/5A	500/5	20 x 12  25 x 10  30 x 10	5	7,5	10
M70329.	TC5.2 600/5A	600/5	20 x 12  25 x 10  30 x 10	5	7,5	10
<b>TC6.2</b>						
M70341.	TC6.2 100/5A	100/5	20 x 20  25 x 12  30 x 10	1,75	3,75	7,5
M70342.	TC6.2 125/5A	125/5	20 x 20  25 x 12  30 x 10	3,75	7,5	10
M70343.	TC6.2 150/5A	150/5	20 x 20  25 x 12  30 x 10	5	7,5	10
M70344.	TC6.2 200/5A	200/5	20 x 20  25 x 12  30 x 10	7,5	10	10
M70345.	TC6.2 250/5A	250/5	20 x 20  25 x 12  30 x 10	7,5	10	15
M70346.	TC6.2 300/5A	300/5	20 x 20  25 x 12  30 x 10	10	10	15
M70347.	TC6.2 400/5A	400/5	20 x 20  25 x 12  30 x 10	10	10	15
M70348.	TC6.2 500/5A	500/5	20 x 20  25 x 12  30 x 10	15	15	20
M70349.	TC6.2 600/5A	600/5	20 x 20  25 x 12  30 x 10	15	20	25
<b>TC6</b>						
M70331.	TC6 150/5A	150/5	30 x 15  20 x 10  40 x 10	1	3,5	5
M70332.	TC6 200/5A	200/5	30 x 15  20 x 10  40 x 10	3,5	5	7,5
M70333.	TC6 250/5A	250/5	30 x 15  20 x 10  40 x 10	5	7,5	10
M70334.	TC6 300/5A	300/5	30 x 15  20 x 10  40 x 10	5	7,5	10
M70335.	TC6 400/5A	400/5	30 x 15  20 x 10  40 x 10	5	7,5	10



## TC12 3200/5A

Current transformers narrow section

Code: M7038C.

CODE	TYPE	Measurement Range (A)	Flat strip(mm)	Class 0,5 Power (VA)	Class 1 Power (VA)	Class 3 Power (VA)
M70336.	TC6 500/5A	500/5	30 x 15  20 x 10  40 x 10	7,5	10	15
M70337.	TC6 600/5A	600/5	30 x 15  20 x 10  40 x 10	7,5	10	15
M70338.	TC6 750/5A	750/5	30 x 15  20 x 10  40 x 10	10	15	20
M70339.	TC6 800/5A	800/5	30 x 15  20 x 10  40 x 10	10	15	20
<b>TC8.3</b>						
M703B1.	TC8.3 250/5A	250/5	20 x 25  30 x 20  40 x 10	10	15	20
M703B2.	TC8.3 200/5A	200/5	20 x 25  30 x 20  40 x 10	10	15	25
M703B3.	TC8.3 300/5A	300/5	20 x 25  30 x 20  40 x 10	15	20	25
M703B4.	TC8.3 400/5	400/5	20 x 25  30 x 20  40 x 10	15	20	25
M703B5.	TC8.3 500/5	500/5	20 x 25  30 x 20  40 x 10	15	20	25
M703B6.	TC8.3 600/5	600/5	20 x 25  30 x 20  40 x 10	15	20	25
M703B7.	TC8.3 750/5	750/5	20 x 25  30 x 20  40 x 10	20	25	30
M703B8.	TC8.3 800/5	800/5	20 x 25  30 x 20  40 x 10	25	30	35
M703B9.	TC8.3 1000/5	1000/5	20 x 25  30 x 20  40 x 10	25	30	35
<b>TC8</b>						
M7036C.	TC8 200/5A	200/5	50 x 30  60 x 12	1	2,5	5
M7036B.	TC8 300/5A	300/5	50 x 30  60 x 12	2,5	5	7,5
M70361.	TC8 400/5A	400/5	50 x 30  60 x 12	5	7,5	10
M70362.	TC8 500/5A	500/5	50 x 30  60 x 12	7,5	10	15
M70363.	TC8 600/5A	600/5	50 x 30  60 x 12	10	15	20
M70364.	TC8 750/5A	750/5	50 x 30  60 x 12	15	20	25
M70365.	TC8 800/5A	800/5	50 x 30  60 x 12	15	20	30
M70366.	TC8 1000/5A	1000/5	50 x 30  60 x 12	15	20	30
M70367.	TC8 1200/5A	1200/5	50 x 30  60 x 12	15	20	30
M70368.	TC8 1500/5A	1500/5	50 x 30  60 x 12	15	20	30
M70369.	TC8 1600/5A	1600/5	50 x 30  60 x 12	15	20	30
M7036A.	TC8 1250/5A	1250/5	50 x 30  60 x 12	15	20	30
<b>TC10</b>						
M7037F.	TC10 200/5	200/5	50 x 50  60 x 30  80 x 30	1	2,5	5
M7037D.	TC10 300/5A	300/5	50 x 50  60 x 30  80 x 30	2,5	5	7,5
M7037G.	TC10 400/5	400/5	50 x 50  60 x 30  80 x 30	2,5	5	7,5
M7037B.	TC10 500/5A	500/5	50 x 50  60 x 30  80 x 30	5	7,5	10
M7037C.	TC10 600/5A	600/5	50 x 50  60 x 30  80 x 30	7,5	10	15
M7037H.	TC10 750/5	750/5	50 x 50  60 x 30  80 x 30	7,5	10	15
M70372.	TC10 800/5A	800/5	50 x 50  60 x 30  80 x 30	7,5	10	15
M70373.	TC10 1000/5A	1000/5	50 x 50  60 x 30  80 x 30	10	15	20
M70374.	TC10 1200/5A	1200/5	50 x 50  60 x 30  80 x 30	10	15	20
M7037E.	TC10 1250/5A	1250/5	50 x 50  60 x 30  80 x 30	10	15	20



## TC12 3200/5A

Current transformers narrow section

Code: M7038C.

CODE	TYPE	Measurement Range (A)	Flat strip(mm)	Class 0,5 Power (VA)	Class 1 Power (VA)	Class 3 Power (VA)
M70375.	TC10 1500/5A	1500/5	50 x 50  60 x 30  80 x 30	15	20	25
M70376.	TC10 1600/5A	1600/5	50 x 50  60 x 30  80 x 30	15	20	25
M70377.	TC10 2000/5A	2000/5	50 x 50  60 x 30  80 x 30	15	20	25
M70378.	TC10 2500/5A	2500/5	50 x 50  60 x 30  80 x 30	15	20	30
M70379.	TC10 3000/5A	3000/5	50 x 50  60 x 30  80 x 30	15	20	30
<b>TC12</b>						
M7038B.	TC12 800/5A	800/5	100 x 50	10	15	20
M70381.	TC12 1000/5A	1000/5	100 x 50	10	15	20
M70382.	TC12 1200/5A	1200/5	100 x 50	10	15	20
M7038D.	TC12 1250/5A	1250/5	100 x 50	10	15	20
M70383.	TC12 1500/5A	1500/5	100 x 50	15	20	30
M70384.	TC12 1600/5A	1600/5	100 x 50	15	20	30
M70385.	TC12 2000/5A	2000/5	100 x 50	15	20	30
M70386.	TC12 2500/5A	2500/5	100 x 50	20	30	40
M70387.	TC12 3000/5A	3000/5	100 x 50	30	40	60
M7038C.	TC12 3200/5A	3200/5	100 x 50	30	40	60
M70388.	TC12 4000/5A	4000/5	100 x 50	35	40	60

For other configurations see table of additional features



## TC12 3200/5A

Current transformers narrow section

Code: M7038C.

### Dimensions

