



GEDE EDC-T 4G

GEDE EDC-T 4G, PRIME PLC Concentrator

Code: Q67550. DESCATALOGADO

- > 2nd transformer connection: No
- > Homologation: Naturgy
- > Communications: PRIME | 4G
- > Digital inputs: -
- > LV supervisor: 1

Description

The **COMPACT DC** concentrator is the device used to manage and read three-phase and single-phase power meters connected to the same low-voltage network using PRIME communications.

Typically located in the transformer substation, the **COMPACT DC** concentrator provides telemanagement features for the meters, whether reading the information they provide, or executing the actions that can be applied to this type of device, such as modifying tariffs, actuating the circuit breaker, etc.

COMPACT DC has an indirect three-phase meter with low-voltage monitoring functions, depending on the model.

The device features PRIME PLC communications, an Ethernet port and digital inputs.



GEDE EDC-T 4G

PLC PRIME Concentrator

Code: Q67550.

Specifications

AC power supply

Consumption	10 ... 26 VA
Frequency	50 / 60 Hz
Nominal voltage	110 ... 230 V~ ±20 %

Mechanical characteristics

Size (mm) width x height x depth	203 x 120 x 130 (mm)
Envelope	Self-extinguishing V0 plastic
Fastening	DIN rail
Weight (kg)	1,2

Environmental characteristics

Protection class	IP40
Relative humidity (without condensation)	5 ... 95 %
Storage temperature	-30 ... + 80 °C
Operating temperature	-25 ... +70 °C

Current measurement circuit

Nominal current (In)	5 A
----------------------	-----

Voltage measurement circuit

Maximum input voltage consumption	0.07 VA
-----------------------------------	---------

Communication Network

Technology / Interface	PRIME
------------------------	-------

Standards

Electrical safety, Maximum height (m)	2000
Standards	UNE-EN 61000-4-2, UNE-EN 61000-4-3, UNE-EN 61000-4-4, UNE-EN 61000-4-5, UNE-EN 62052-11, IEC 61010

User interface

LED	15 indication LEDs / 1 LED (20000 imp / kWh) / 1 LEDs (20000 imp / kVArh)
-----	---

Radio communication

Band	Cuatribanda/HSPA+HSPA/UMTS 850/900/1900/2100 MHz
Technology / Type	4G (Huawei MU609)



GEDE EDC-T 4G

PLC PRIME Concentrator

Code: Q67550.

GEDE EDC
PRIME PLC Concentrator

CODE	TYPE	2nd transformer connection	Homologation	Communications	Digital inputs	LV supervisor
Q67560.	GEDE EDC-T 4G BAT	No	-	PRIME 4G	-	1
Q67000.	GEDE EDC	No	-	PRIME	-	No
Q67550.	GEDE EDC-T 4G	No	Naturgy	PRIME 4G	-	1
Q67540.	GEDE EDC-T 4I	No	Naturgy	PRIME	4	1
Q675A0.	GEDE EDC-T 4I/4O	No	Naturgy	PRIME	4	1
Q67500.	GEDE EDC-T	No	Naturgy	PRIME	-	1
Q67570.	GEDE EDC-2T	Yes	Naturgy	PRIME	4	2
Q67080.	GEDE EDC TGU	No	Iberdrola	PRIME	-	1