



CR-50

CR-50, Tester wyłączników i przekaźników, 50 A (walizkowy),

Kod: P6021100A0000 DESCATALOGADO

Opis

The CR-50, CR-100 and CR-250 units include specially designed current generation systems that can check the current / time trigger curve of automatic switches and indirect protection relays. Its operation principle is based on the injection of an alternating current that can be adjusted throughout the circuit being tested with a short-circuit cable loop. The connection of an auxiliary contact of the switch being tested can be used to measure the trip time for each current selected. The test is easily carried out with a start-stop control. An automatic meter is responsible for taking the measurements and showing them on the display. We can highlight that the unit can be used to check the full protection system, including the current transformer in the case of indirect relays, since the current can be injected on the primary side of these transformers. After the test, a digital display automatically shows the value of the current injected and the trip time until the RESET button is pressed.



CR-50

Tester wyłączników i przekaźników zabezpieczeniowych

Kod: P6021100A0000

Okular

Zasilanie prądem zmiennym

Zużycie	1,6 A máx
Częstotliwość	50 ... 60 Hz.
Napięcie znamionowe	230 V ~ ± 10 % - 15 %

Właściwości mechaniczne

Wymiary (mm) szer. x wys. x głębok.	320 x 200 x 215 (mm)
Waga (kg)	12

Właściwości elektryczne

Maksymalny prąd fazowy	50 A
------------------------	------

Obwód pomiarowy prądu

Dopuszczalne nadmierne obciążenie	1,5 In (1min)
Prąd maksymalny	0 ... 99.9 (A)

Interfejs użytkownika

Typu display	7 segmentów LED
Maksymalna wartość	99999,9 s

Precyzja pomiaru

Precyzja	1 % ± 2 digits
----------	----------------

CR

Tester wyłączników i przekaźników zabezpieczeniowych

KOD	TYP	Opis
Tester przekaźników		
P6021100A0000	CR-50	Tester wyłączników i przekaźników, 50 A (walizkowy)
P6021200A0000	CR-100	Tester wyłączników i przekaźników, 100 A (walizkowy)
P6021300A0000	CR-250	Tester wyłączników i przekaźników, 250 A
Akcesoria		
P69903.	Trafo 2500 para CR-250	Transformator 2500 A dla CR-250
P69902.	Cable 1,5M/2500A	Kabel
P69901.	MPC-CR	Wózek transportowy CR250

Obejmuje certyfikat laboratorium CIRCUTOR